

8 CHANNEL EMBED DeEMBED + AFD INSERTION MODEL SED-858



- ◆ HD/SD SDI Video In
- ◆ AFD Pass-thru
- ◆ Analog-AES Audio I/O
- ◆ 8 CH Embed
- ◆ AFD Delete
- ◆ AFD Auto Insert
- ◆ 8 CH DeEmbed
- ◆ Remove All Audio
- ◆ Analog I/O Level Cont
- ◆ Embed Audio Delay
- ◆ AFD Display
- ◆ Anc Detect/Delete
- ◆ Save Multi Config
- ◆ AES Audio Detect
- ◆ Dolby E Compatible
- ◆ AFD Insert0

The SED-858, is a one RU chassis, that can embed/de-embed audio and monitor/insert AFD (Active Format Description, SMPTE 2016-1), ancillary data in an SDI signal. The video input can be SD-SDI (SMPTE 259M), or HD-SDI (SMPTE 292M), and is auto detected. The SED-858 will embed or de-embed up to eight audio channels (4 AES inputs), into/from two groups in the horizontal ancillary region of the SD (SMPTE 272M-C), or HD (SMPTE 299M) output signal. This unit is compatible with progressive segmented frame video, and automatically generates the Payload Identifier (SMPTE 352M), on the video output.

The SED-858 includes 8 input and output channels of: AES balanced, AES unbalanced, balanced analog, AES embed (input), and AES de-embed (output). The digital inputs are auto detected and sample rate converted to 48 KHz for embedding. The analog inputs are received in pairs and converted into 4 AES streams, with a volume control included for both inputs and outputs. The inputs, including de-embed, can be assigned, in 8 channel groups by type, to any of the outputs, excluding embed. Any mix of 4 inputs, including de-embed, can be embedded into the video output. An 8 channel embed re-mixer allows mixing control over single channels, including mute. Individual embedded AES streams can be delayed up to 1 second. Embedding and de-Embedding may be performed simultaneously, and use 24-bit AES audio processing, (inputs may be 20-bit).

Existing embedded audio can be deleted, replaced, or passed through, but matching group's channels will be replaced. This allows one unit to embed 8 channels to groups 1 and 2, and a second unit could embed an additional 8 channels to groups 3 and 4.

The AFD data can be monitored, inserted, deleted, or auto inserted, (insert only if no AFD detected). The AFD setting and the line number to insert the data on are entered by the user. All the non-audio ancillary data types present in the input video can be displayed by their DID/SDID codes, and up to 4 of them, selected by the user, can be removed from the output video.

The SED-858 set-up features are controlled by a rotary encoder, and displayed on a VFD, with most functions accessible using front panel buttons. LEDs on the front panel show the status of the unit at a glance. 4 presets may be used, with changes saved into flash, for multiple configurations. Each unit requires chassis specific breakout cables that expand the number of available connections beyond what would fit on a standard plug-in card system. The breakout connectors include two 25 pin male and one 25 pin female that provides for AES and analog audio I/O. The unit ships with one cable for AES Balanced. The other cables for analog audio I/O are optional items and should be purchased separately.

LINK ELECTRONICS, INC.

2137 Rust Avenue
Cape Girardeau, MO 63703
Phone: 573 334 4433
FAX: 573 334 9255

HD SD SDI EMBEDDER De-EMBEDDER MODEL SED-858

INPUT:

SDI Video: 270Mb/s and 1.485Gb/s

AES:

Balanced: . . . 8 Channel (4 AES3-1992) 25 Pin D-Sub, Requires Cable Adapter Assy. for XLR Inputs
 Level: 1V Minimum, 110 Ω
 Unbalanced: 8 Channels, 4 BNCs AES3-ID 75 Ω BNC
 Level: 800mV to 1.2V
 Sample Rates: 48 KHz

Analog:

Balanced: 8 Channel 25 Pin D-Sub Connectors, Requires Cable Adapter Assy. for XLR Inputs
 Impedance: 110 Ω
 Connector: 25 Pin D-Sub, Requires Adapter Cable Assembly for XLR
 Common Mode Rejection Ratio: >55db
 Signal-to-Noise Ratio: >60db

OUTPUTS:

AES:

Balanced: 8 Channel (4 AES3-1992) 25 Pin D-Sub, Requires Cable Adapter Assy. for XLR Outputs
 Level: 4.2 volts p-p typical at 110 Ω
 Unbalanced: 4 AES3-ID 75 Ω BNC
 Level: 1V p-p typical at 75 Ω
 Sample Rate: 48 KHz
 Coupling: DC
 Jitter: <0.01UI

Analog:

Balanced: . . . 8 Channel 25 Pin D-Sub Connectors, Requires Cable Adapter Assy. for XLR Outputs
 Impedance: 600 Ω
 Connector: 25 Pin D-Sub, Requires Adapter Cable Assembly for XLR

FRONT PANEL CONTROLS:

3 embed all options: Lit Momentary Push Button
 6 menu selects: Lit Momentary Push Button
 Bypass: Lit Momentary Push Button
 Readout of timing adjustments: VFD Display
 Data Select: Rotary Encoder

ENVIRONMENTAL:

Temperature 0c to 50cC Ambient
 Humidity: 10% to 90% non-condensing
 Power; 3W

MECHANICAL:

Height: 1.75 Inches
 Width 19.0 Inches
 Length: 10 Inches
 Weight: 3 Pounds

Specifications and designs are subject to change at any time without notice.



LINK ELECTRONICS, INC. 2137 Rust Avenue Cape Girardeau, MO 63703-7668
 Phone 573 334 4433 ♦ FAX 573 334 9255

Available At: VMI, Inc.
 www.vmivideo.com

SF Bay Area - 408-745-1700
 Central California - 916-369-6911
 Southern California - 714-894-6100

Western Washington - 425-778-1330
 Eastern Washington - 509-532-0118
 Oregon - 503-222-0034